

#### Is Now Part of



### ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo



### **BD244/A/B/C**

# Medium Power Linear and Switching Applications

• Complement to BD243, BD243A, BD243B and BD243C respectively



1.Base 2.Collector 3.Emitter

Rev. A, February 2000

### **PNP Epitaxial Silicon Transistor**

#### Absolute Maximum Ratings $T_C=25^{\circ}C$ unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>CBO</sub>	Collector-Base Voltage		
	: BD244	- 45	V
	: BD244A	- 60	V
	: BD244B	- 80	V
	: BD244C	- 100	V
V <sub>CEO</sub>	Collector-Emitter Voltage		
	: BD244	- 45	V
	: BD244A	- 60	V
	: BD244B	- 80	V
	: BD244C	- 100	V
V <sub>EBO</sub>	Emitter-Base Voltage	- 5	V
I <sub>C</sub>	Collector Current (DC)	- 6	А
I <sub>CP</sub>	*Collector Current (Pulse)	- 10	А
I <sub>B</sub>	Base Current	- 2	А
P <sub>C</sub>	Collector Dissipation (T <sub>C</sub> =25°C)	65	W
T <sub>J</sub>	Junction Temperature	150	°C
T <sub>STG</sub>	Storage Temperature	- 65 ~ 150	°C

#### Electrical Characteristics T<sub>C</sub>=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units		
V <sub>CEO</sub> (sus)	* Collector-Emitter Sustaining Voltage					_		
	: BD244	$I_C = -30 \text{mA}, I_B = 0$	- 45			V		
	: BD244A		- 60			V		
	: BD244B		- 80			V		
	: BD244C		- 100			V		
I <sub>CEO</sub>	Collector Cut-off Current : BD244/244A	$V_{CE} = -30V, I_{B} = 0$			- 0.7	mA		
	: BD244B/244C	$V_{CE} = -60V, I_{B} = 0$			- 0.7	mA		
I <sub>CES</sub>	Collector Cut-off Current : BD244	$V_{CE} = -45V, V_{BE} = 0$			- 0.4	mA		
	: BD244A	$V_{CE} = -60V, V_{BE} = 0$			- 0.4	mA		
	: BD244B	$V_{CE} = -80V, V_{BE} = 0$			- 0.4	mA		
	: BD244C	$V_{CE} = -100V, V_{BE} = 0$			- 0.4	mA		
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{EB} = -5V, I_{C} = 0$			- 1	mA		
h <sub>FE</sub>	* DC Current Gain	$V_{CE} = -4V, I_{C} = -0.3A$	30					
		$V_{CE} = -4V, I_{C} = -3A$	15					
V <sub>CE</sub> (sat)	* Collector-Emitter Saturation Voltage	$I_C = -6A, I_B = -1A$			- 1.5	V		
V <sub>BE</sub> (on)	* Base-Emitter ON Voltage	$V_{CE} = -4V, I_{C} = -6A$			- 2	V		
* Pulse Test: PW =	* Pulse Test: PW =300μs, duty Cycle =2% Pulsed							

2000 Fairchild Semiconductor International

## **Typical Characteristics**




Figure 1. DC current Gain




Figure 3. Collector-Emitter Saturation Voltage




Figure 5. Power Derating





Figure 2. Base-Emitter Saturation Voltage





 $V_{\text{CE}}[V], \, \text{COLLECTOR-EMITTER} \, \, \text{VOLTAGE}$ 

Figure 4. Safe Operating Area

### **Package Demensions**

### TO-220





10.00 ±0.20

Dimensions in Millimeters